

Venue Specs Orangehouse**Update 01/2026**

- PA:** KS 3-way active, processor controlled:
2x T11
4x TW Mk2
- Stagbox & Multicore:** 32 Channel Send + 8 Channel Return; Subsnake Stage left 8 Channel
2x CAT 7 S/FTP with Ethercon from FOH to Stage
- FOH:**
- Mixingdesk: Allen & Heath SQ7
96kHz FPGA Processing, 48 Input Channels, DEEP Processing Ready,
12 Stereo Mixes + LR, 3 Stereo Matrix, 8 Stereo FX Engines +
Dedicated Returns, 32x32 Dante Card, 32x32 USB Audio Interface
- MONITOR:**
- Floor: 4x Syrincs SM12 (12"/1")
Drumfill: 2x Martin F 15 (15"/1,4")
Amping: 2x Crest Audio 4801
1x Crest Audio 7001 (Drumfill)
- MICS:**
- | | |
|------------------|--------------------------|
| 3x Shure SM58 | 1x Shure Beta 91 |
| 1x Shure Beta 58 | 3x Sennheiser e604 |
| 4x Shure SM57 | 3x AKG CK391 |
| 1x Shure Beta 57 | 6x Palmer PAN02 DI Aktiv |
| 1x Shure Beta 52 | |
- POWER:**
- Backline: 1 separate powercircuit with 16A and RCD
- light & sound are on separate phases**
- STAGE:** Length: 5,5m, Height: 0,5m, Depth: 5m,
Stage to ceiling-height: 3m

No Drumriser available**Sound check is only possible from 6 p.m.!**

LIGHT:

Board: 1x Work Lightshark LS1 plus Touchscreen

Dimmerpack: 1x Ultralite D1225 12x 10A angesteuert über DMX512

Luminaires:

Stage: 6x Expolite TourLED XCR 50
8x Expolite TourLED MC60
2x Expolite TourLED MC180
2x Expolite Tourspot 150 Mini (LED SPOT)
4x Stufenlinsen (1kW) (Frontlight)
4x Expolite TourLED MC60 (Frontlight)
2x Epolite TourBlinder 100

Dancefloor: 6x Expolite TourLED XCR 50
4x Expolite ELW MC7 (LED Wash)
1x Strobe 1,5kW DMX
6x UV LS-Tubes

Atmo: 4x Epolite TourBar 64
4x Cameo Q-Spot 40 RGBW (Mirrorball)
1x Cameo Root Par TW (Merch)
6x Cameo Root Par TW (Buffet)
1x Cameo Q-Spot 40 TW (Bar)

VIDEO:

Projectors: 1x Optoma Eh401 Beamer 4000 Ansi-Lumen (stage)
1x ACER H5370BD Beamer 2500 ANSI-Lumen (site)

Signal: HDMI via HDBaseT (Cat5) to both Projectors either from stage or FOH

1 rollabel Screen in Backtruss (2,95 wide; 2,50 high)

1 rollabel Screen left side, next to stage (2,95 wide; 2,50 high)

DJ-booth next to FOH:

1x Urei 1603 DJ-Mixer
2x Technics 1210 MKII
1x DAP Audio DS 2200D Dual CD Player

Because of firesafety-instructions it's not allowed to use Fogmachines!

On any further question, please call **Feierwerk** Technik:

Hansastr. 39 | D-81373 München | Fon 089/72488 – 142 | Mail: technik@feierwerk.de

DEKO MATERIAL, BACKDROP:

Please note for all shows and all venues!

The fire behaviour of all deco materials according to German DIN 4102 part 1 or DIN EN 13501 must be verified by a test certificate. All deco materials, fabrics etc. have to be of low flammability (B1). Certificates have to be available in German language! The Certificates for Germany have to be provided by a German institution!

SOUND LIMIT ACCORDING TO GERMAN LAW DIN 15905-5

(DIN, the German institute for standardization by agreement with the German federal government)

DIN 15905-5 event – technology – sound engineering – part 5: Measure to prevent the risk of hearing loss of the audience by high sound exposure of. Electroacoustic sound systems

SOUNDLIMIT $L_r = 99\text{dB(a)}$ measured on the average at the loudest area within 30 minutes

CONFETTI:

Confetti have to be of low flammability as other deco material or backdrops. (DIN 4102 part 1 or DIN EN 13501 see above).

The use of confetti has to be clarified in advance


Extra cleaning costs will apply!

Orangehouse
N: 175.75 qm

E 5
Stuhllager
N: 11.64 qm

Zuluftschacht

Bühne
+0.50



Scheinwerfer



Expolite TourLED 50XCR



DTS Scena 1000




Expolite TourLED MC180



Strobe 1,5 KW



Expolite TourLED MC60



Expolite TourBar 64



Expolite TourSpot 150 mini



Cameo QSpot 40 RGBW



Expolite TourBlinder 100



Cameo QSpot 40 TW



Expolite ELW MC7 Zoom



Cameo ROOT Par TW

Device	DMX Channel	Mode	Breaker	Offset Plugbox	Hotpatch No.	Description
Dimmer 1 - PC 1	1-001			D13	19	Fronttruss
Dimmer 1 - PC 2	1-002			D14	20	Fronttruss
Dimmer 1 - PC 3	1-003			D15	21	Fronttruss
Dimmer 1 - PC 4	1-004			D16	22	Fronttruss
Dimmer 1	1-005				23	
Dimmer 1	1-006				24	
Dimmer 1	1-007					
Dimmer 1	1-008					
Dimmer 1	1-009					
Dimmer 1	1-010					
Dimmer 1	1-011					
Dimmer 1	1-012					
Expolite Tourspot 150 mini	1-013	14 Ch		F17	Patch3	Backtruss
Expolite Tourspot 150 mini	1-027	14 Ch		F18	Patch3	Backtruss
Expolite ELW 7 MC	1-041	20 Ch		F9	Patch5	Sidetruss DF1
Expolite ELW 7 MC	1-061	20 Ch		F9	Patch5	Sidetruss DF1
Expolite ELW 7 MC	1-081	20 Ch		F1	Patch5	Sidetruss DF2
Expolite ELW 7 MC	1-101	20 Ch		F1	Patch5	Sidetruss DF2
Expolite TourLed MC180 Zoon	1-121	SSP 9CH		21	17	Backtruss
Expolite TourLed MC180 Zoon	1-130	SSP 9CH		21	17	Backtruss
Expolite TourLed MC60 Zoon	1-139	SSP 9CH		18	14	Sidetruss
Expolite TourLed MC60 Zoon	1-148	SSP 9CH		18	14	Sidetruss
Expolite TourLed MC60 Zoon	1-157	SSP 9CH		17	13	Sidetruss
Expolite TourLed MC60 Zoon	1-166	SSP 9CH		17	13	Sidetruss
Expolite TourLed MC60 Zoon	1-175	SSP 9CH		18	14	Sidetruss
Expolite TourLed MC60 Zoon	1-184	SSP 9CH		18	14	Sidetruss
Expolite TourLed MC60 Zoon	1-193	SSP 9CH		17	13	Sidetruss
Expolite TourLed MC60 Zoon	1-202	SSP 9CH		17	13	Sidetruss
Expolite TourLed MC60 Zoon	1-211	SSP 9CH		9	9	Fronttruss
Expolite TourLed MC60 Zoon	1-220	SSP 9CH		10	10	Fronttruss
Expolite TourLed MC60 Zoon	1-229	SSP 9CH		10	10	Fronttruss
Expolite TourLed MC60 Zoon	1-238	SSP 9CH		9	9	Fronttruss
Expolite 50XCR	1-247	AR2.S 6CH		19	15	Backtruss
Expolite 50XCR	1-253	AR2.S 6CH		20	16	Backtruss
Expolite 50XCR	1-259	AR2.S 6CH		22	18	Backtruss
Expolite 50XCR	1-265	AR2.S 6CH		22	18	Backtruss
Expolite 50XCR	1-271	AR2.S 6CH		20	16	Backtruss
Expolite 50XCR	1-277	AR2.S 6CH		19	15	Backtruss
Expolite 50XCR	1-283	AR2.S 6CH		8	8	DF1
Expolite 50XCR	1-289	AR2.S 6CH		8	8	DF1
Expolite 50XCR	1-295	AR2.S 6CH		1	1	DF2
Expolite 50XCR	1-301	AR2.S 6CH		2	2	DF2
Expolite 50XCR	1-307	AR2.S 6CH		4	4	DF2
Expolite 50XCR	1-313	AR2.S 6CH		3	3	DF2
Strobo 1,5 KW DMX	1-319	2 Ch		F5		DF2
Expolite Tourbar 64	1-322	5 Ch		5	5	Ambient
Expolite Tourbar 64	1-327	5 Ch		5	5	Ambient
Expolite Tourbar 64	1-332	5 Ch		5	5	Ambient
Expolite Tourbar 64	1-337	5 Ch		5	5	Ambient
Expolite TourBlinder 100	1-342	1 Ch		7	7	Fronttruss
Expolite TourBlinder 100	1-344	1 Ch		7	7	Fronttruss
Cameo Q-Spot 40 RGBW	1-346	9 Ch		F11	Patch1	Mirrorball DF1
Cameo Q-Spot 40 RGBW	1-355	9 Ch		F11	Patch1	Mirrorball DF1
Cameo Q-Spot 40 RGBW	1-364	9 Ch		F3	Patch1	Mirrorball DF2
Cameo Q-Spot 40 RGBW	1-373	9 Ch		F3	Patch1	Mirrorball DF2
Cameo Rootpar TW - Merch	1-458	2 Ch		F15	Patch8	Merch-Light
Cameo Rootpar TW - Buffet	1-459	2 Ch		F14	Patch7	Buffet-Light
Cameo Rootpar TW - Buffet	1-460	2 Ch		F14	Patch7	Buffet-Light
Cameo Rootpar TW - Buffet	1-461	2 Ch		F14	Patch7	Buffet-Light
Cameo Rootpar TW - Buffet	1-462	2 Ch		F8	Patch7	Buffet-Light
Cameo Rootpar TW - Buffet	1-463	2 Ch		F8	Patch7	Buffet-Light
Cameo Rootpar TW - Buffet	1-464	2 Ch		F8	Patch7	Buffet-Light
Cameo Q-Spot 40 TW	1-465	2 Ch		F6	Patch4	Bar
UV Tube 40W	-	-		F13	Patch6	DF1
UV Tube 40W	-	-		F13	Patch6	DF1
UV Tube 40W	-	-		F13	Patch6	DF1
UV Tube 40W	-	-		F4	Patch6	DF2
UV Tube 40W	-	-		F4	Patch6	DF2
UV Tube 40W	-	-		F4	Patch6	DF2